

Screen

1.1 Check & Unpack



Before anything (!) Carefully inspect the received package(s) for outside marks, dents, bumps, tears, holes etc. Anything that may indicate transport damage to the screen (The panels are very fragile for damages and even a small damage can make it useless).

Take pictures with your smartphone if anything even appear suspicious to document an unopened damaged box. Without documentation, it is very difficult to claim a refund from transporter or vendor.

1.2 Mount (correctly)



Follow the instruction on how to mount the screen using proper equipment and accessories. Professional screens are normally possible to mount both in Landscape and Portrait mode (Ventilation is made for that).

But do ensure you are doing it the right way, "upside down" will negatively impact the ventilation and reduce the screens lifetime. Warranty may even be void.

Follow instructions in the documentation that came with the screens.

1.3 Install OMNIplay



When power is connected, either the screen will start up directly (**if pre-configured**) and show Databeat *OMNIplay startup screen*. If it only shows a light (typically red), it is ready (**but NOT pre-configured**). If so, turn on the screen and follow the *prepare for* and install *OMNIplay* for your respective device. When this is done, *OMNIplay* will start up.

Player

2.1 Connect (Power & Network)



Now we will connect the screen to power and internet. If you are using **OMNIpower** please ensure the SIM card is installed in the **OMNIpower device**, and that you have the phone number available (you will add this later).

Put OMNIpower device between the powersocket and the Screen's power cable. Follow the instructions to connect screen to Internet, via cable or WLAN.



2.2 Add LicenseKey



Ensure that the correct licence key is/has been assigned in order to link it to the correct location (**Very important !**).

Use the *screen remote control* (Check that batteries are installed correctly).

Press **#0** to add/change License key.

2.3 Verify (it is Playing)



With **OMNIplay** installed and the correct **License key** applied, the screen should start right up to the default channel, and play the content.

If everything is OK, you are ready to move the screen to production.

Production

3.1 Select Channel



Use the screen **remote control** (typically the Channel up/down button) to select which channel to play on the specific screen. A list of available channels will be displayed on the screen. Bear in mind, new content may need to be downloaded to the screen, before it starts to play.

Verify that your screen is playing normally and playing the content as it should.

3.2 Move to Production



The screen will be in *Delivery Mode* and needs to be in *Production mode*. On your **remote control** press **#1** to access an on-screen UI to :

- 1) Add OMNIpower phonenumber (if relevant)
- 2) ensure that OMNIpower is working by testing it.
- 3) Verify the Location address and contact information and
- 4) Confirm that setup is done and move it to production, so that support can track and follow the screen in operation.

3.3 Document & Enjoy



On your **remote control**, press **#5** and you will see a big text with core information. Use your Smartphone, and please take 2-3 good pictures of the screen, showing how it is placed on the location, and send it to the E-mail address : ScreenDoc@Databeat.Net

Before you leave, send text to Databeat support at +47 41 41 04 71 and wait for confirmation